□□□□

□□□□	SFENG
□□□□	SF-P125
□□□□□□	□□
□□□	□□
□	SUS□□□□□□□
□□□□□□	200□□□
□□□□	6.30□0.2480 ''□
□□□□□	□5□a□
□□□□□	50□□□□W
□□□	3.17□0.1248 ''□
□□□□□□	2.40□0.0945 ''□/ 2.45□0.0965 ''□
MOQ	100 □
□□□□□□	7 □□□□□□□□□□□□□

□□□□□

SF-P125

SF-R125-VCR



SF-R125-VSC



SF-R125-CR



SF-R125-SC



SF-P125-E



Probe specifications SF-P125(技术规格)

- Recommended minimum center(最小间距):
  3.17mm(.1248 ")
- Mounting hole size(钻孔尺寸):
  压克力：2.40mm(.0945 ")
  电木板、玻璃纤维板：2.45mm(.0965 ")
- Full travel(行程)：6.30(.2480 ")
- Spring force(弹簧压力)：200g
- Materials and finishes(材料及涂饰):
  Plunger:Be Cu,Rh plated;
  Barrel:Brass,Gold plated
  Spring:Stainless steel
- Current ration(额定电流)：5A(安培)
- Contact resistance(接触电阻)：50mΩ(毫欧姆)
- Connectioins(接线形式):
  Crimp：R125-VCR,R125-CR
  Solder cup：R125-VSC、R125-SC

www.shengfengdz.com

[illegible]

1.[illegible] 24[illegible]

2.[illegible] [illegible]OEM[illegible]

3.[illegible] [illegible]

4.[illegible] [illegible]

[illegible]

PCB[illegible]ICT[illegible]FCT[illegible]

[illegible]2[illegible]&[illegible];[illegible]

BGA[illegible]·[illegible]

□□□□□□□□□□□□QZ□VZ□□□□□LM□□□□□□□□□□□□□□□

□□□□□□□□□□□□□□□□□□□□□□□;

□□□□□&□038;□□□□□□□/□□□□□

□□□□□□□□□□□□□□30□OK□□□□□□□□□□□□POM□□□□□□□□□□□

□□□□

Spring exhausted tester	DC power supply	Current resistance tester
Microscope	Tensile strength tester	Spring tester

□□□□□□□□


胜峰电子